



BRAVO Lite

**100+ KM
RANGE**



Rise Bravo Lite

Motor Capacity	1,500 W
Battery Capacity	76.8 V 30 Ah
Range	100 km
Battery Chemistry	LFP
Cell Format	24 S
Other Battery Spec.	SOC percentage on display, Mobile App
Charging Cycles	2000
Charger	87.6 V 7 A
Charging time	4 - 5 hr
Controller	32 A
Max. Speed	50 km/h
Brake (Front/Rear)	Disc/Disc
Light (Head/Parking/Signal/Tail)	(LED/LED/LED/LED)
Display	LED
Wheel size and Tire	Front: 3.00 - 10 Rear: 3.00 - 10
Anti-theft system	Yes
Remote	Smart Key
Max. Loading	200 kg
Consumption (kWh)	2.71
Ground Clearance	135 mm
Other Options	Reverse gear, Parking gear, Traction Control System, Hill Assist Mode
Seat Height	755 mm




4 YEAR WARRANTY

03 YEAR REPLACEMENT + 01 YEAR SERVICE

Why Choose Lithium-ion Batteries

- Over 2000 charging cycles (800 Charging Cycles for Lead-Acid)
- Lead Poisoning – Brain Damage and Impact on the Nervous System
- High energy density (Li-ion: 150 kW/kg; Lead-acid: 35 Wh/kg)
- High Depth of Discharge (Li-ion: 80%; Lead-acid: 50%)
- Higher C-rate
- Higher efficiency
- In-built Battery Management System



warranty

Battery – 03 years

Motor – 02 years*

Frame – 02 years**

Charger – 01 year

Motor Controller – 01 years

DC-DC Converter – 06 months

Instrument Cluster – 06 months

2000+
Charging Cycles



Specifications of the Battery Pack
Rated Voltage: 76.8 V
Rated Capacity: 30 Ah
Charging Voltage: 87.6 V

Rs:

* Conditions Apply